



**Europäisches
Patentamt**

**European
Patent Office**

**Office européen
des brevets**

#3

Jc960 U.S. PRO
09/758302



Bescheinigung

Certificate

Attestation

Die angehefteten Unterla-
gen stimmen mit der
ursprünglich eingereichten
Fassung der auf dem näch-
sten Blatt bezeichneten
europäischen Patentanmel-
dung überein.

The attached documents
are exact copies of the
European patent application
described on the following
page, as originally filed.

Les documents fixés à
cette attestation sont
conformes à la version
initialement déposée de
la demande de brevet
européen spécifiée à la
page suivante.

Patentanmeldung Nr. Patent application No. Demande de brevet n°

00300268.0

Der Präsident des Europäischen Patentamts;
Im Auftrag

For the President of the European Patent Office

Le Président de l'Office européen des brevets
p.o.

I.L.C. HATTEN-HECKMAN

DEN HAAG, DEN
THE HAGUE, 26/10/00
LA HAYE, LE

THIS PAGE BLANK (USPTO)



Europäisches
Patentamt

European
Patent Office

Office européen
des brevets

Blatt 2 der Bescheinigung
Sheet 2 of the certificate
Page 2 de l'attestation

Anmeldung Nr.:
Application no.:
Demande n°: 00300268.0

Anmeldetag:
Date of filing:
Date de dépôt: 14/01/00

Anmelder:
Applicant(s):
Demandeur(s):
LUCENT TECHNOLOGIES INC.
Murray Hill, New Jersey 07974-0636
UNITED STATES OF AMERICA

Bezeichnung der Erfindung:
Title of the invention:
Titre de l'invention:

Adaptive code-tracking RAKE receiver for direct-sequence code-division multiple access (cdma) communications

In Anspruch genommene Priorität(en) / Priority(ies) claimed / Priorité(s) revendiquée(s)

Staat:
State:
Pays:

Tag:
Date:
Date:

Aktenzeichen:
File no.
Numéro de dépôt:

Internationale Patentklassifikation:
International Patent classification:
Classification internationale des brevets:

H04B1/707

Anmeldetag benannte Vertragstaaten:
Contracting states designated at date of filing: AT/BE/CH/CY/DE/DK/ES/FI/FR/GB/GR/IE/IT/LI/LU/MC/NL/PT/SE
Etats contractants désignés lors du dépôt:

Bemerkungen:
Remarks:
Remarques:

See for title page 1 of the description

THIS PAGE BLANK (USPTO)

14-01-2000

EP00300268.0

DESC

99LUC1571EPP

Lucent Technologies

Adaptive Code-Tracking Receiver for Direct-Sequence Code-Division Multiple Access (CDMA) Communications over Multipath Fading Channels and Method for Signal Processing in a Rake Receiver

5

Description

10 Field of the Invention

The invention is directed to a method of signal processing in a rake receiver and to a direct-sequence code division multiple access (DS-CDMA) receiver in general and especially to a direct-sequence code division multiple access (DS-CDMA) receiver for mobile cellular communications.

15

Prior Art

Spread-spectrum communications systems have been used for many decades, at first because of the excellent anti-jamming properties, but lately because of several advantages in multiple-access scenarios such as cellular communications. In a spread-spectrum system, pseudo-noise code signals (PN code) are used to modulate the data signal, where the bandwidth of the former is substantially larger than that of the latter. The PN code can be used to modulate the carrier frequency, called frequency-hopped spread spectrum (FH), or it can be multiplied directly with the information signal, called direct-sequence spread-spectrum (DS). The resulting signal then has a bandwidth far broader than that of the original

20

25

data signal.

In the following, only DS-spread-spectrum signals and systems are addressed in the prior art discussion. One field of applications for such systems is e.g. mobile cellular communications. Recent worldwide standardization efforts defined DS-spread-spectrum as the transmission method of choice for third-generation mobile telecommunication systems. Orthogonal PN-codes are assigned to different users transmitting simultaneously in the same frequency band, enabling receivers to detect and decode their users' signal despite interference from other users. Other impairments in the mobile environment include the fading multipath channel and Doppler frequency shift due to mobile motion.

Presently employed spread-spectrum receivers gather as much of the transmitted signal energy as possible in order to maximize the signal-to-noise ratio. In order to do so, the received signal is synchronously correlated with the known PN-code to yield the original information signal. In multipath fading channels however, the signal energy is dispersed over a certain amount of time due to distinct echo paths and scattering. One crucial task of the receiver is thus to estimate the channel to improve its performance. In realizable digital communication receivers, the principle of Synchronized detection is employed, see f.i. Heinrich Meyr, Marc Moeneclacy and Stefan Fechtel in "Digital Communication Receivers: Synchronization, Channel Estimation and Signal Processing", John Wiley and Sons, New York, 1998, meaning that estimates for channel parameters are computed and used in the detection process as if they were the true values. This generally results in a small loss in performance compared to the case where one has perfect knowledge about

the channel, but that loss becomes negligible if the data after channel decoding are compared. If the receiver has information about the channel profile, one way of gathering signal energy is then to assign several correlator branches to different echo paths and combine their outputs constructively, a structure known as the rake receiver.

The rake receiver has several fingers, one for each echo path, and in each finger, the path delay with respect to some reference delay such as a direct or the earliest received path, must be estimated and tracked throughout the transmission. The tracking unit generates estimates for the delays of several multipath components by means of an early-late timing error detector and utilizes these estimates for the different delays either to shift the phase of the pseudonoise-code (PN-code), or to compute intermediate samples of the data signal at the estimated timing instants.

However, tracking of such delays in general suffers from interference from the other paths and becomes troublesome and difficult, especially when echo paths lie close together, meaning that their arrival times at the receiver differ by values in the order of the chip duration T_c , being the inverse of the PN-code signal bandwidth.

Several algorithms have been proposed in the past for tracking of the multipath delays. All of these algorithms suffer from either high sensitivity to multipath fading and thus reduced performance in such environments, or implementation complexity which is prohibitive for the use in mobile terminals where size, production costs and power consumption are critical issues. One example of the former is the so-called early-late gate timing error detector (EL-TED),

14-01-2000

EP00300268.0

DESC

being a natural solution to a mathematical optimization problem for nondispersive, additive white Gaussian noise channels (AWGN) (see Heinrich Meyr, Marc Moeneclacy and Stefan Fechtel in "Digital Communication Receivers: Synchronization, Channel Estimation and Signal Processing", John Wiley and Sons, New York, 1998, Heinrich Meyr and Gerd Ascheid in "Synchronization in Digital Communications", vol. 1, John Wiley & Sons, New York, 1990 and A. J. Viterbi in "CDMA - Principles of Spread Spectrum Communication", Addison-Wesley Publishing Company, Reading (MA), 1995).

A prior art early-late gate timing error detector usually is able to track echo path delay as long as the relative delay between two paths is larger than some threshold. However, if the relative delay is smaller than a certain threshold value, the early-late gate timing error detector is not apt to longer distinguish the two paths. Furthermore, tracking of weaker paths (lower power) can be disturbed by stronger paths with a relative delay larger than the aforementioned threshold. For an example of an algorithm with significantly higher implementation complexity than the early-late gate timing error detector, see R. A. Iltis, "An EKF-Based Joint Estimator for Interference, Multipath, and Code Delay in a DS Spread-Spectrum Receiver", IEEE Transactions on Communications, Vol. 42, No. 2/3/4, February-April 1994.

Especially in indoor mobile communication scenarios, the path delay of the last identifiable echo path is small compared to outdoor scenarios. All of the signal energy is dispersed around the path with the shortest delay and a sufficient echo path resolution is critical for adequate receiver performance, expressed for instance as the bit-error rate (BER). None of the existing early-late gate timing error

14-01-2000

EP00300268.0

DESC

5

detector algorithms with reasonable complexity is able to track adjacent path delays which are separated by less than the mentioned threshold. With such a tracking system, the required signal-to-noise ratio to achieve a certain BER is reduced significantly.

Consequently, it is an object of the invention to provide a direct-sequence code division multiple access (DS-CDMA) receiver and a method for signal processing in a rake receiver having an improved tracking performance, especially in cases where delay differences of arriving signal components of multipath signals are in the order of the chip duration.

According to the invention and in order to significantly reduce the effect of multipath disturbance on the timing error detector, several early and late correlators are used and their outputs are adaptively weighted.

The timing error detector can be coherent or noncoherent - in the former case, the adaptive weighting of correlators is identical to pre-filtering the spread-spectrum signal with an adaptive finite impulse response (FIR) filter, followed by only one correlator. In the noncoherent case, two adaptive filters and two correlators are required.

The invention is described below in more detail and with reference to the appended drawings in view of most preferred embodiments.

30

Brief Description of the Drawings

- Figure 1 shows the general structure of a digital code-tracking loop for each finger in a rake receiver for DS-spread-spectrum communications;
- Figure 2 shows the conventional coherent early-late gate timing error detector, embedded in a code-tracking loop for one finger in a rake receiver;
- Figure 3 shows the conventional noncoherent early-late gate timing error detector, embedded in a code-tracking loop for one finger;
- Figure 4 illustrates the concept of adaptively weighting several early and late correlator branches within the timing error detector;
- Figure 5 shows a coherent implementation of the new adaptive early-late gate timing error detector, using one adaptive FIR filter in the synchronization path
- Figure 6 shows a noncoherent implementation of the new adaptive early-late gate timing error detector, using two adaptive FIR filters and two correlators;
- Figure 7 shows the detector characteristic for a conventional coherent early-late timing error detector;
- Figure 8 shows one possible detector characteristic for the new modified adaptive early-late timing error detector in its coherent version;
- Figure 9 shows a two dimensional plot of the characteristics of outer finite impulse response filter taps;
- Figure 10 shows an error signal S-curve for EL extension with a zero-crossing at $\tau = \pm 2T_c$;
- Figure 11 shows an error signal S-curve for EL extension with a zero-crossing at $\tau = \pm T_c$;

14-01-2000

EP00300268.0

DESC

7

Figure 12 shows timing tracking estimates for a conventional timing error detector based on an indoor scenario with a spreading factor $SF=4$, moving speed of receiver 10 km/h and a chip duration $T_c = 1 \text{ sec} / 3,84 \cdot 10^6$;

Figure 13 shows timing tracking estimates for an inventive simple adaptive timing error detector based on an indoor scenario with values $SF=4$ and a moving receiver having a speed of about 10 km/h and a chip duration $T_c = 1 \text{ sec} / 3,84 \cdot 10^6$;

Figure 14 shows timing tracking estimates for an inventive MMSE adaptive timing error detector based on an indoor scenario with values $SF=4$ and a moving receiver having a speed of about 10 km/h and a chip duration $T_c = 1 \text{ sec} / 3,84 \cdot 10^6$;

Figure 15 shows a two dimensional plot of tracking performance values for different timing error detectors;

Figure 16 shows the detection path of a rake receiver model for a detailed theoretical discussion thereof;

Figure 17 a noncoherent delay locked loop model for a detailed theoretical discussion thereof;

Figure 18 a coherent delay locked loop model for a detailed theoretical discussion thereof.

Detailed Description of the Invention

The invention is explained in more detail and in view of preferred embodiments below where like numerals are designating similar elements in different embodiments of the invention.

14-01-2000

EP00300268.0

DESC

8

The invention is part of a tracking device for a digital spread-spectrum rake receiver 1 as shown in Figures 1 and 16.

The incoming signal 2 is fed through a pulse matched filter 3, matched to the transmission pulse. An analog-to-digital (A/D) converter 4 generates equidistant samples 5 of the pulse matched filtered signal and feeds them to a digital interpolator/decimator 6, which generates intermediate samples 7, 8 of the same signal at the estimated timing instants \hat{t} for each of the N rake fingers 9, 10, 11.

The interpolated signal is fed to the detection path 7, where the correlation with the PN-code 16 and symbol detection takes place in each finger 9, 10, 11 as shown in more detail Figure 16 where essentially only the detection path 7 is shown.

Furthermore, the signal 8 is fed to several timing error detectors 12 which generate error signals 13 that are proportional to the remaining path delay error in the signal of the respective Rake finger 9, 10, 11. These error signals are lowpass-filtered in the loop filter to yield estimates for the respective path delay, again for each rake finger 9, 10, 11, which are then fed back to the interpolator/decimator 6, closing the tracking loop 15. The timing error detector 12 is modified adaptively for each finger 9, 10, 11, using channel state information such as the powers, the signal-to-noise ratios and the delays of all paths assigned to the respective rake fingers 9, 10, 11. It is noted that instead of interpolating and decimating the data signal for each rake finger 9, 10, 11, the PN-code can just as well be shifted in order to guarantee the correct alignment between data samples and PN-code samples.

Furthermore, due to normally very slowly varying path delays, delay tracking of all fingers 9, 10, 11 can be implemented in time-sharing using only one dedicated tracking structure.

5

Conventional Timing Error Detectors

Conventional early-late timing error detectors are depicted in Figures 2 and 3 in the coherent and noncoherent versions, respectively. The structure downstream of the digital
10 interpolator/decimator 6 is replicated for each rake finger 9, 10, 11, whereas the interpolator/decimator 6 is used jointly. The samples 5 of the incoming signal $z(t = nT_s)$ with T_s being the time interval between two samples are interpolated and decimated at the estimated timing delay
15 $\hat{\tau}$ for each finger 9, 10, 11. Two data streams 7, 8 are generated, one is fed to the detection path 7 and the other 8 is fed to the synchronization path 15. There, the samples and a shifted version thereof, spaced $\pm T_c/2$ with respect to the samples in the detection path, are correlated in a correlator
20 17, 18 with the PN-code, yielding early 20 and late 19 estimates of the transmitted symbols.

In the coherent case as shown in Figure 2, early 20 and late 19 estimates, are subtracted by a subtraction unit 21 and
25 multiplied by a multiplier 22 with reconstructed transmitted symbols 23.

The reconstructed symbols 23 can be generated by complex conjugately multiplying symbol decisions or pilot symbols
30 with estimates of the channel phase or the channel phasor. The real part of the resulting samples, now on symbol rate $1/T$, is then the error signal x , 13 and is fed through loop

1.0

filter 14 with lowpass characteristic to yield the estimate for the timing delay $\hat{\tau}$.

In the noncoherent case as shown in Figure 3, the square of the absolute value of early and late symbols is computed by absolute squaring elements 24, 25 and subtracted to yield the error signal x , 13. For references, see also A. Wilde in "Extended tracking range delay-locked loop", Proceedings of the International Conference on Communications, Seattle, USA, 1995 and Volker Aue and Gerhard P. Fettweis in "A Non-Coherent Tracking Scheme for the RAKE Receiver That Can Cope With Unresolvable Multipath", Proceedings of the International Conference on Communications, Vancouver, Canada, 1999.

15

The inventive adaptive Timing Error Detector Concept

The concept of the new adaptive timing error detector is depicted in Figure 4 for the coherent case. Instead of using one early and one late correlator 17, 18, several early and late correlators 26, 27, 28 are employed. The digital interpolator/decimator 6 again feeds the correct samples at rate $1/T_c$ to the detection path 7. The synchronization path 8 is fed with samples at rate M/T_c .

20

The shifted versions thereof in the following branches of correlators 26, 27, 28 may be aligned symmetrically in an early-late fashion with respect to the detection path 7, as in the conventional case, or alternatively shifted in the causal or noncausal direction.

25
30

In either case the samples in each branch 7, 8 are correlated with the PN-code 16 and adaptively weighted such as to minimize the effect of other multipaths tracked in the rake

14-01-2000

EP00300268.0

DESC

11

receiver 1.

For $M = 1$, $\lambda_1 = -1$, $\lambda_2 = 1$, this inventive embodiment reduces to the conventional timing error detector. The signal
5 processing after summation of all branches of correlators 26, 27, 28 is identical to the conventional timing error detector, both in the coherent and the noncoherent case.

A structure with more than two correlators in an early-late
10 delay tracking loop was presented in "Extended tracking range delay-locked loop", Proceedings of the International Conference on Communications, Seattle, USA, 1995. However, there the weights of the different correlator branches were solely chosen so as to maximize the tracking range of the
15 loop. No effort was made to adaptively combat interference from adjacent paths and their respective rake fingers.

The idea of pre-filtering the spread-spectrum signal was addressed by R. Sampaio-Neto and R. A. Scholtz in
20 "Precorrelation Filter Design for Spread-Spectrum Code Tracking in Interference", IEEE Journal on Selected Areas in Communications, Vol. SAC-3, No. 5, September 1985. There, however, fixed pre-correlation filters were employed in an analog system and no effort was made to specifically and
25 adaptively combat multipath interference.

For the inventive coherent timing error detector, the adaptive weighting of several correlation branches corresponds to the adaptive finite impulse response (FIR)
30 filtering model in Figure 5.

Due to the linearity of the correlation operation, the weighting and summation can be performed prior to correlating

14-01-2000

EP00300268.0

DESC

12

with the PN-code 16, yielding a much simplified structure with only one correlator and one adaptive filter 29, the taps 30 of which being identical to the weighting factors 31, 32, 33 in Figure 4.

5

For the noncoherent timing error detector 12, an equivalent model is depicted in Figure 6. The transition from a bank of adaptively weighted correlators to a single correlator branch cannot be done here due to the nonlinear nature of the absolute-square operation in squaring elements 24, 25.

10

However, an extension of the conventional non-coherent timing error detector is to also include adaptive FIR filters 29a, 29b in both early and late correlator 17, 18 branches and to jointly optimize their weights so as to minimize multipath interference.

15

Adaptive FIR Filter Design

The aim of adaptively filtering the data samples in the synchronization path 8 of each finger 9, 10, 11 is to minimize effects of other paths of the multipath signal have on the detector characteristic of the path tracked by the respective rake finger 9, 10 or 11 of rake receiver 1.

20

A typical detector characteristic for the conventional coherent timing error detector, also called S-curve, is depicted in Figure 7. Let's denote the current path and as such the current rake finger by its index i , then Figure 7 shows the expected value of the error signal x_i , 13 for an AWGN channel, i.e. for a channel including additive white Gaussian noise (AWGN), and a raised-cosine pulse-matched filter autocorrelation function as a function of the τ in the respective finger 9, 10, 11.

25

30

14-01-2000

EP00300268.0

DESC

13

The timing error detector of rake finger i is influenced by adjacent multipaths lying everywhere but in the zero-crossings of the S-curve as for a value of zero no additional contribution arises for this path having a delay resulting in a zero value.

Assuming perfect channel knowledge, meaning a perfect knowledge of path delays τ_i and powers as well as signal-to-noise ratios, the detector characteristic for each path of the received multipath signal 2 can be designed adaptively by pre-filtering the synchronization path samples, either by generating nulls at the other path locations, or by jointly minimizing an adequate cost function.

15

In the first case, an additional path j with a delay relative to the current path i which coincides with a zero-crossing of the S-curve of path i does not contribute to the error signal $(x, 13)$ of the actual rake finger with path i being associated to the respective actual rake finger 9, 10 or 11.

20

For the new adaptive timing error detector, one possibility of computing filter coefficients is to perform a constrained linear optimization, where the constraints are given by the zero-crossing of the S-curve at $\tau = 0$, in order to keep the tracker unbiased, and by the normalization of the slope of the S-curve in the origin to some constant.

25

The task solved by the timing error detector control 34 shown in Figure 1 is then to find the finite impulse response (FIR) of filter 29 $\lambda = [\lambda_1 \dots \lambda_L]$ which jointly minimizes the sum

30

14-01-2000

EP00300268.0

DESC

14

of the mean-square of the detector characteristic of the current path at the locations of all other paths and the estimator variance induced by the channel AWGN, being proportional to the filter energy (in the case of an AWGN channel and $M = 1$). The calculated result depends on the length of the FIR filter, L , on the amount and location of the other paths and on the Doppler frequency spread.

Another possibility, with reduced complexity compared to the first inventive embodiment, comprises to extend the conventional timing error detector by one weighted correlator e.g. as shown in Figure 4 by numerals 28, 33 (or FIR filter taps) so as to "shift" the first zero-crossing left or right of the origin of the S-curve in Figure 7 to a desired location where the influence of the contribution of the error signal 13 of other paths is reduced. With this last mentioned algorithm one adjacent path of the multipath signal 2 can be considered in the optimization process, resulting in a loss in performance compared to the first scheme at significantly reduced implementation complexity.

The magnitude of the additional correlator is a function of the desired zero-crossing; it can be stored in memory and accessed online, depending on the location of the closest (or strongest) adjacent path.

Between these two inventive embodiments, a tradeoff between performance and complexity is possible.

Description of further preferred Embodiments

A further preferred inventive embodiment comprises advanced timing tracking algorithms and methods for an UMTS rake Receiver. It can be shown that conventional tracking

14-01-2000

EP00300268.0

DESC

15

algorithms for the channel tap delays in a multipath channel environment, in the form of early-late gate delay-locked loops (EL-DLL), are error-prone in the case that adjacent paths are less than about $1.5 \cdot T_c$ apart, T_c being the chip duration. In that case, the timing estimates of rake fingers assigned by a central control unit tend to merge, resulting in a loss of lock of both fingers. It can also be shown that significant performance gains can be expected if the "path resolution" can be increased. This is due to the fact that the signal energy dispersed on the multipath channel can be gathered more efficiently by the rake receiver.

By adaptively pre-filtering the signal in the synchronization path of the timing error detector (TED), the expected value of the error signal (S-curve) of the timing error detector of each path can be shaped so as to minimize interference of adjacent paths, according to some optimization criterion. Different optimization methods allow a tradeoff between performance and implementation complexity.

20

Detailed theoretical Approach in View of preferred Embodiments

A rake receiver for CDMA communications in the downlink must be able to accurately acquire and then track the multipath channel parameters for the desired user during the entire duration of the transmission.

The timing tracking algorithms are particularly sensitive to a sufficiently large multipath separation, because if that is not guaranteed, delay estimates in the rake receiver belonging to paths lying "close" together in the delay domain will interfere with one another, causing the estimates to merge. This means a loss-of-lock for both rake fingers,

30

making a reacquisition necessary. Minimum path separations were determined to be about $1,5 T_c$ for the coherent, data-aided and decision and phasor directed early-late timing error detector, and about $1,75 T_c$ for the noncoherent, non-
 5 data-aided early-late timing error detector.

However, these limitations are of a severely reduced influence for the inventive systems.

10 Especially in indoor scenarios however, showing a low delay-spread, the assignment and subsequent tracking of rake fingers lying closer together than the mentioned thresholds has shown to yield significant performance gains, i.e. about 5dB for an indoor scenario with a delay spread of about $2 T_c$
 15 and a spreading factor SF of 4.

If the acquisition and control unit (path searcher) is thus able to assign rake fingers to paths which lie close together, an adequate tracking scheme which prevents fast
 20 loss-of-lock is provided by the invention.

Transmission Model and Timing Error Characteristic

25 Signal model

The baseband-equivalent transmitted CDMA signal for one user can be expressed as

(1)

$$s(t) = \sum_{k=-\infty}^{\infty} a_{\lfloor \frac{t}{T_c} \rfloor} d_{k \bmod N} g_T(t - kT_c),$$

14-01-2000

EP00300268.0

DESC

17

with

(2)

- a_n : data symbol sent at time instant n
- N_c : spreading factor
- N_s : effective spreading sequence length
- $\mathbf{d} = [d_0 \cdots d_{N_s-1}]$: effective spreading sequence
- $g_T(t)$: root-raised cosine TX pulse
- T_c : chip duration, for UTRA, $T_c = 244.14$ ns

5

The multipath fading channel is given by

(3)

$$h(t; \tau) = \sum_{l=0}^{N_p-1} c_l(t) \delta(\tau - \tau_l(t))$$

10 with τ being the relative path delay and t the absolute time variable, respectively.

The discrete-time model for the rake receiver is depicted in Figures 16. The received signal is given by

15

(4)

$$r(t) = s(t) * h(t; \tau) + n(t)$$

where $*$ denotes convolution and $n(t)$ includes additive white Gaussian noise (AWGN) and other-user interference. The signal
 20 is pulse-matched filtered and fed to several rake fingers 9, 10, 11, ideally one for each resolvable path of the received multipath signal. In each finger 9, 10, 11, the estimated

14-01-2000

EP00300268.0

DESC

18

path delay $\hat{\tau}$, is compensated for, followed by multiplication with the spreading sequence 16 and summation over one symbol period. Finally, the decorrelated signals from each finger 9, 10, 11 are input to the rake combiner or summation unit 37, which maximizes the signal to noise ratio (SNR) at the output by multiplying the signals with the optimal combiner coefficients, being the complex conjugate of the estimated instantaneous channel phasors, normalized to the overall channel energy.

Timing Error Detectors

The pulse matched-filtered signal $z(t)$ is sampled at twice the chiprate and input to a digital interpolator 6, whose task is to compensate for the estimated timing offset $\hat{\tau}$. At its output, the data is demultiplexed: the "even" samples are fed to the detection path 7, whereas the "odd" samples are input to the tracking path 8 - we get two data streams at $1/T_c$. In the tracking path 8, the data and a shifted version of thereof are decorrelated with the spreading sequence 16. In the noncoherent version, the data samples (now on symbol rate $1/T$), are absolute-squared and subtracted, yielding the error signal 13. In the coherent version, the samples are subtracted prior to correlation, correlated and multiplied with complex conjugate maximum-likelihood symbol estimates, created by multiplying symbol decisions or pilot symbols with channel phasor estimates. The real part of the resulting signal yields the error signal 13. In either case, the error signal is fed through a loop filter 14 with lowpass characteristic to yield the timing estimate.

Timing Error Detector Error Characteristic

The expected value of the error signal x , 13 for the coherent timing error detector, also called S-Curve, is depicted in

Figure 7 for an AWGN channel and a raised-cosine pulse-matched filter autocorrelation function. The S-Curve is an open-loop characteristic, meaning that feedback effects are not accounted for. The normal point of operation is when the
5 estimated delay τ lies around the origin. A small deviation from zero will generate an error signal which is used in the feedback loop to drive the delay error back to zero. If the channel is nondispersive, meaning that there is only one propagation path, then the error signal is a function of that
10 one path only.

However, if one or several other paths exist in the channel model, then they will contribute to the error signal, increasing the noise level by a factor proportional to their
15 tap power and to the square of the value of the S-Curve at their location. If the S-Curve is equal to zero at those locations, then those additional paths will have no influence on the error signal on average. The basic idea of minimizing the influence of adjacent paths is thus to "reshape" the
20 characteristic such that it has zero-crossings at the locations of adjacent paths. This can be achieved by pre-filtering the signal in the synchronization path 8 and it will be further outlined in the following discussion.

25 Interference Minimization by adaptive pre-Filtering and Structure of the new Timing Error Detector

The concept of the new adaptive timing error detector is depicted in Figure 4 for the coherent case. Instead of using one early and one late correlator, several early and late
30 correlators are employed. The digital interpolator/decimator 6 again feeds the correct samples at rate $1/T_c$, to the detection path. The synchronization path is fed with samples at rate M/T_c . The shifted versions thereof in the following

14-01-2000

EP00300268.0

DESC

20

correlator branches may be aligned symmetrically in an early-late fashion with respect to the detection path 7, as in the conventional case, or alternatively shifted in the causal or noncausal direction. In either case the samples in each
5 branch are correlated with the PN-code 16 and adaptively weighted such as to minimize the effect of other multipaths tracked in the rake receiver.

For the coherent timing error detector, the adaptive
10 weighting of several correlation branches corresponds to the adaptive finite impulse response (FIR) filtering model in Figure 5. Due to the linearity of the correlation operation, the weighting and summation can be performed prior to correlating with the PN-code 16, yielding a much simplified
15 structure with only one correlator 26 and one adaptive filter 29, the taps of which being identical to the weighting factors 31, 32, 33 in Figure 4. For the noncoherent timing error detector, an equivalent model is depicted in Figure 6. The transition from a bank of adaptively weighted correlators
20 to a single FIR/correlator branch cannot be done here due to the nonlinear nature of the absolute-square operation. However, a natural extension of the conventional non-coherent timing error detector is to also include adaptive FIR filters in both early and late correlator branches and to
25 jointly optimize their weights so as to minimize multipath interference.

Adaptive Filter Design

The design of the adaptive FIR filters offers a tradeoff
30 between performance in terms of lock-in-behavior and complexity. Under the assumption of perfect channel knowledge, meaning path delays and powers as well as signal-to-noise ratios, the detector characteristic for each path

can be designed adaptively by pre-filtering the synchronization path samples, either by generating nulls at the other path locations, or by jointly minimizing an adequate cost function.

5

Constrained linear Optimization

For the new adaptive timing error detector, one possibility of computing filter coefficients is to perform a constrained linear optimization, where the constraints are given by the zero-crossing of the S-curve at $\tau = 0$, in order to keep the tracker unbiased, and by the normalization of the slope of the S-curve in the origin to some constant. The task is then to find the FIR filter $\lambda = [\lambda_1 \dots \lambda_L]$ which jointly minimizes the sum of the mean-square of the detector characteristic of the current path at the locations of all other paths and the estimator variance induced by the channel AWGN, being proportional to the filter energy (in the case of an AWGN channel and $M = 1$). The result depends on the length of the FIR filter L , on the amount and location of the paths and on the Doppler frequency spread. For general references on linear optimization, see e.g. D. G. Luenberger, "Optimization by vector-space methods", John Wiley and Sons, 1969 and R. Fletcher, "Practical methods of optimization", John Wiley and Sons, 1987. Define a cost function $V(\lambda)$ to be

25

(5)

$$V(\lambda) = \|A\lambda\|^2 + \|\lambda\|^2 = \lambda^T(A^T A + I)\lambda$$

where the matrix A is $(N_p \times L)$ and contains the mean-square contribution of each path at each FIR filter tap location:

30

(6)

$$\mathbf{A} = \begin{pmatrix} A_{1,1} & \dots & A_{1,L} \\ \vdots & \ddots & \vdots \\ A_{N_p,1} & \dots & A_{N_p,L} \end{pmatrix}$$

$$A_{i,j} = c_i \cdot \gamma \cdot g(\tau_i - \delta_j).$$

c_i is the root-mean square (rms) power of path i, normalized
 5 to the total power, γ is the overall rms signal to noise
 ratio (SNR) and δ_j is the j-th filter tap location, relative
 to the detection path sample. For the example in Figure 10,
 $\delta = [-1,5, -0,5, 0,5, 1,5]$. τ and δ are normalized to the
 chip duration.

10

Due to the fact that the chips are essentially uncorrelated
 after descrambling, $\|\lambda\|^2 = \sum_{i=1}^L \lambda_i^2$. \mathbf{I} is the $(L \times L)$ identity
 matrix. The aim is now to minimize cost function $V(\lambda)$,
 subject to the constraints mentioned above:

15

(7)

$$\min_{\lambda} \{V(\lambda) : \mathbf{D}\lambda = \mathbf{f}\} = \min_{\lambda \in F} V(\lambda)$$

$$F = \mathbf{D}^+ \mathbf{f} + \mathbf{N}[\mathbf{D}]$$

20

The matrix \mathbf{D} is $(2 \times L)$ and contains the expression for the
 zero crossing of the timing error detector characteristic at
 $\tau = 0$ and its slope at the same location:

$$\mathbf{D} = \begin{pmatrix} D_{1,1} & \dots & D_{1,L} \\ D_{2,1} & \dots & D_{2,L} \end{pmatrix}$$

$$D_{1,j} = g(t = \delta_j) \quad (8)$$

$$D_{2,j} = \left. \frac{\partial}{\partial t} g(t) \right|_{t=\delta_j} \quad (9)$$

$g(t)$ is the pulse-matched filter autocorrelation function, $\mathbf{f} = [0 \ c]^T$ describes the two conditions, c being the constant slope at the origin. \mathbf{D}^+ is the pseudoinverse of \mathbf{D} and $\mathbf{N}[\mathbf{D}]$ is its nullspace. The idea is now to move from a constrained optimization to an unconstrained one. To that end, the first step is to reduce the dimensionality of the problem. A singular value decomposition of \mathbf{D} yields

10

$$\mathbf{D} = \mathbf{P} \mathbf{S} \mathbf{Q}^T, \quad (10)$$

where \mathbf{P} is $(N_p \times N_p)$ and \mathbf{Q} is $(L \times L)$. \mathbf{S} is of the form

$$\mathbf{S} = \begin{pmatrix} \hat{\mathbf{D}} & \dots & 0 \\ \vdots & \ddots & \vdots \\ 0 & \dots & 0 \end{pmatrix} \quad (11)$$

where $\hat{\mathbf{D}}$ is $(v \times v)$, and diagonal ($v \leq \min(N_p, L)$). The nullspace of \mathbf{D} is equal to the range of a matrix \mathbf{H} , being

15

defined as

$$\mathbf{H} = [\mathbf{q}_{v+1} \ \dots \ \mathbf{q}_n] \quad (12)$$

with the \mathbf{q}_i being the indexed columns of \mathbf{Q} . This identity yields the new unconstrained optimization problem

14-01-2000

EP00300268.0

DESC

24

$$\min_{\theta \in \mathbb{R}^N} V(D^+f + H\theta) \quad (13)$$

Inserting $\lambda = D^+f + H\theta$ into (5) yields

$$\begin{aligned} V(\lambda) &= (D^+f + H\theta)^T (A^T A + I) (D^+f + H\theta) \\ &= \|D^+f\|^2 + 2f^T (D^+)^T (A^T A + I) H\theta + \theta^T H^T (A^T A + I) H\theta \\ &=: \|D^+f\|^2 + B^T \theta + \frac{1}{2} \theta^T C \theta \end{aligned} \quad (14)$$

This is a quadratic form in θ . Solving for θ finally yields

$$\theta = -C^+ B \quad (15)$$

with

$$\begin{aligned} B &= (2f^T (D^+)^T (A^T A + I) H)^T \\ C &= 2H^T (A^T A + I) H \end{aligned}$$

5

the FIR filter λ is then given by $\lambda = D^+f + H\theta$. An example for a resulting S-curve in this case is shown in Figure 8. Here, 3 paths have been assumed at relative delays of $\tau_1 = 0$, $\tau_2 = T_c$ and $\tau_3 = 2T_c$, with root mean-square powers of 0 dB, -10 dB and -20 dB, respectively.

10

It is easily seen that the contributions of the two paths adjacent to the one at the origin are nulled out by the zero-crossings of the S-curve at their respective locations. It is seen in the magnified region that the detector characteristic for path 1 is nearly zero at the location of the two other paths. It is also noted that the lock-in range of the delay tracking loop, being the region from $\tau = 0$ to the first zero-crossing in either direction, is physically constrained by pre-filtering the synchronization path samples.

20

14-01-2000

EP00300268.0

DESC

25

Reduced Complexity Optimization

A sub-optimal method, however, with significantly reduced complexity compared to the first embodiment is to extend the conventional timing error detector by one or two weighted correlators (or FIR filter taps) so as to "shift" the first zero-crossing left or right of the origin of the S-curve in Figure 7 to a desired location. With this algorithm, one adjacent path can be considered in the optimization process, resulting in a loss in performance compared to the first scheme at significantly reduced implementation complexity. The magnitude of the additional correlator is a function of the desired zero-crossing; it can be stored in memory and accessed online, depending on the location of the closest (or strongest) adjacent path.

Consider the case where the early-late structure is extended by two correlators lying $\pm 1,5 T_c$ from the detection sample, i.e. an extension with $M = 1$, $L = 4$ according to Figure 4. The "outer" taps of the adaptive FIR are assumed to be equal in magnitude, but with opposing sign. The inner taps are assumed to be ± 1 , as in the conventional timing error detector structure. With this structure, a zero-forcing condition for the timing error detector characteristic at some location τ can be derived in a straightforward manner. The expected value of the error signal x is given by

$$E[x] = g(T_c/2 + \tau) - g(-T_c/2 + \tau) + \lambda \{g(-3T_c/2 + \tau) - g(3T_c/2 + \tau)\} \quad (16)$$

where $g(t)$ is assumed to be the pulse-matched filter autocorrelation function in the AWGN case. Setting to zero and solving for λ yields (for the AWGN case)

$$\lambda(\tau) = \frac{g(-T_c/2 + \tau) - g(T_c/2 + \tau)}{g(-3T_c/2 + \tau) - g(3T_c/2 + \tau)} \quad (17)$$

Once the exact structure of the timing error detector is
 5 known (M, L), this characteristic depends only on the desired
 location of the zero crossing. It is shown in Figure 9 for
 the structure mentioned above. S-curves for optimized timing
 error detectors are shown in Figures 10 and 11, where
 adjacent paths are assumed to be $2 T_c$ and T_c away,
 10 respectively. The taps indicate the placement and size of the
 EL-FIR filter taps with respect to the detection path sample.

Tracking Performance

Simulated path delay estimates for an indoor channel model,
 15 SF = 4 and a mobile speed of 10 km/h are shown in Figures 12,
 13 and 14 for the conventional timing error detector, an
 adaptive timing error detector with reduced complexity early
 late extension (EL extension) and the above-explained minimum
 mean squared error (MMSE) adaptive timing error detector,
 20 designed using the constrained linear optimization and as
 expressed e.g. in equation 7, respectively.

It is seen that with the conventional timing error detector,
 the first two paths merge fairly quickly and both rake
 25 fingers subsequently track the same resulting path. The
 simple early-late extension is already able to prevent a
 loss-of-lock of any finger, only low-rate fading is seen to
 influence the path delay estimates. For the MMSE adaptive
 timing error detector, it is seen that the tracking jitter
 30 increases for the first path, a consequence of two facts: on
 one hand, the path itself is strong compared to the other
 two, resulting in a large error signal, on the other hand,

14-01-2000

EP00300268.0

DESC

27

due to the large resulting filter taps and as such an increased filter energy, the loop noise is further enhanced for this case.

- 5 The improved tracking behavior for narrowly spaced rake fingers directly translates into a significant performance gain, reflected in Figure 15. It is seen that the inventive receiver gains at least about 4 dB compared to the conventional timing error detector and that the simple and
10 the MMSE optimization perform nearly equally well. An exemplary detection loss with respect to the case with perfect channel estimation (the leftmost curve), resulting from phasor and timing tracking, amounts to 0,8 dB in this particular scenario, equally distributed among the LMS Kalman
15 phasor estimation used here and the adaptive timing tracking.

In general, a significant performance improvement results if the detector characteristics for all rake fingers are adaptively modified according to the inventive concepts.

20

- Using the knowledge of instantaneous multipath delays, powers and SNR (or estimates thereof), filters can be designed for each rake finger which minimize multipath interference as described above. On one hand, more rake fingers can be
25 assigned within a small delay range, because a loss-of-lock will be much less likely due to less or no interference from other paths.

- On the other hand, and as a consequence of the first fact,
30 the effective SNR at the output of the rake receiver will be improved significantly, because more signal energy can be gathered by the rake receiver. Equivalently, the signal to noise ratio (SNR) requirement in order to achieve a certain

14-01-2000

EP00300268.0

DESC

28

bit error rate (BER) will be reduced, especially in indoor or pedestrian scenarios. The necessary computations can be performed at significantly lower processing rates than the chiprate, due to the fact that channel delay dynamics are usually very slow.

Also, the computation of the adaptive filter coefficients in the case of constrained linear optimization can be divided in one part depending solely on the structure of the timing error detector, i.e. the oversampling factor M and the filter length L , and one part depending on the actual instantaneous channel. The former can be computed offline once the structure is known, whereas the latter should be computed in an online fashion.

A tradeoff between computation complexity and adaptivity or adapting ability is possible if e.g. the filter length is kept variable. Also, in contrast to existing solutions, no estimates of instantaneous channel multipath amplitudes and phases are required according to the invention.

14-01-2000

EP00300268.0

CLMS

Claims

1. Rake receiver for spread spectrum signals comprising
5 a plurality of rake fingers (9, 10, 11) each rake finger
being adapted to receive a signal (7, 8) being part of a
multipath signal (2) and associated with a path of the
multipath, said signal (7, 8) having a delay relative to an
10 other signal associated with an other path of the multipath
signal (2),
a summation unit (37) for generating a summation signal
based on the signals received from of at least some of the
rake fingers (9, 10, 11), said summation signal having an
improved signal to noise ratio (SNR) if compared with the
15 signal to noise ratio (SNR) of at least one of the rake
fingers (9, 10, 11),
a timing error detector (12) for detecting an error of a
delay (τ) of the signal (7, 8) of a rake finger (9, 10, 11)
and for generating a timing error signal (x, 13) which is
20 sent to a unit (6) for compensating the error of the
respective delay (τ),
characterized in that said timing error detector (12)
generates a timing error signal (x, 13) based on the signals
(7, 8) associated with paths of the multipath signal of more
25 than one rake finger (9, 10, 11).
2. Rake receiver for spread spectrum signals according to
claim 1, characterized in that said unit (6) for compensating
the error of the respective delay (τ) feeds signals to a
30 detection path (7) and to a synchronization path (8) of each
of the rake fingers (9, 10, 11) said synchronization path
(8) comprising a plurality of correlators (26, 27, 28) for a

correlation of early and late signals said signals being early or late with respect to signals on the detection path (7).

5 3. Rake receiver according to claim 1 or 2, characterized in that said timing error detector (12) generates a timing error signal (x, 13) based on a weighted average value (31, 32, 33) of the correlated signals.

10 4. Rake receiver according to claim 3, characterized in that said correlation signals are generated by an adaptive finite impulse response filter (29) and a single correlator (26).

15 5. Rake receiver according to claim 4, characterized in that the finite impulse response filter (29) is adaptively updated for pre-filtering the synchronization path (8) signal for at least one rake finger such that nulls or zero-crossings are generated for the expected value of the error
20 signal (x, 13) at the location of at least one other path of the multipath signal (2).

6. Rake receiver according to claim 4, characterized in that said finite impulse response filter (29) is updated
25 adaptively for pre-filtering synchronization path (8) signals such that a cost function is minimized for the expected value of the error signal (x, 13).

7. Rake receiver according to one of claims 1 to 6,
30 characterized in that said adaptively updating is a time variant adjustment of said finite impulse response filter (29) for pre-filtering synchronization path (8) signals to compensate a delay (τ) of the signal of a rake finger being a

time variant delay (τ) of a fading multipath signal.

8. Rake receiver according to one of claims 1 to 6, characterized in that said adaptively updating is a time
5 variant adjustment of said weighted correlated signals (31, 32, 33) to compensate a delay (τ) of the signal of a rake finger (9, 10, 11) being a time variant delay (τ) of a fading multipath signal.

10 9. Rake receiver according to one of claims 1 to 8, characterized in that said timing error detector (12) is an early late gate error timing detector and early and late estimates are subtracted and multiplied with reconstructed transmitted symbols (23).

15

10. Rake receiver according to claim 9 characterized in that said reconstructed symbols (23) are generated by complex conjugately multiplying symbol decisions or pilot symbols with estimates of the channel phase or the channel phasor.

20

11. Rake receiver according to claims 9 or 10 characterized in that the real part of the signal resulting from early and late estimate subtraction and multiplication with the reconstructed transmitted symbols (23) is the generated error
25 signal x .

12. Rake receiver according to one of claims 1 to 11 characterized in that said error signal (x , 13) is fed through a loop filter with lowpass characteristic to yield an
30 estimate $E(x)$ for the timing delay (τ).

14-01-2000

EP00300268.0

CLMS

32

13. Method for signal processing in a rake receiver for multipath spread spectrum signals

said rake receiver comprising a plurality of rake fingers (9, 10, 11) each rake finger being adapted to receive
5 a signal (7, 8) being part of a multipath signal (2),

associating rake fingers (9, 10, 11) with a signal of a path of the multipath signal, said signal (7, 8) of said associated path having a delay (τ) relative to an other signal of an other path of the multipath (7, 8) signal,

10 generating a summation signal based on the signals received from of at least two of the rake fingers (9, 10, 11), said summation signal having an improved signal to noise ratio (SNR) if compared with the signal to noise ratio (SNR) of at least one of the rake fingers (9, 10, 11),

15 detecting an error of a delay (τ) of a signal of a rake finger (9, 10, 11) and generating a timing error signal (x, 13) which is sent to a unit (6) for compensating the error of the respective delay (τ),

characterized by

20 generating said timing error signal (x, 13) based on signals (7, 8) associated with paths of the multipath of more than one rake finger (9, 10, 11).

14. Method for signal processing in a rake receiver for spread spectrum signals according to claim 13,

25 characterized in that said unit (6) for compensating the error of the respective delay (τ) feeds signals to a detection path (7) and to a synchronization path (8) of each of the rake fingers (9, 10, 11), said synchronization path
30 (8) comprising a plurality of correlators (26, 27, 28) for a correlation of early and late signals said signals being early or late with respect to signals on the detection path

(7).

15. Method for signal processing in a rake receiver according to claim 13 or 14,

5 characterized in that said timing error signal (x, 13) is generated based on a weighted average value (31, 32, 34) of the correlated signals.

16. Method for signal processing in a rake receiver

10 according to claim 15,

characterized in that said correlation signals are generated by an adaptive finite impulse response filter (29) and a single correlator (26).

15 17. Method for signal processing in a rake receiver according to claim 16,

characterized in that said finite impulse response filter (29) is adaptively updated for pre-filtering the

20 synchronization path (8) signals such that nulls or zero crossings are generated for the expected value of the error signal (x, 13) at the location of at least one other path of the multipath signal.

18. Method for signal processing in a rake receiver

25 according to claim 16,

characterized in that said finite impulse response filter (29) is adaptively updated for pre-filtering synchronization path (8) signals such that a cost function is minimized for the expected value of the error signal (x, 13).

30

19. Method for signal processing in a rake receiver

according to one of claims 13 to 18,

characterized in that said adaptively updating is a time

14-01-2000

EP00300268.0

CLMS

34

variant adjusting of said finite impulse response filter (29) for pre-filtering synchronization path (8) signals to compensate a delay (τ) of the signal of a rake finger being a time variant delay (τ) of a fading multipath signal.

20. Method for signal processing in a rake receiver according to one of claims 1 to 6, characterized in that said adaptively updating is a time variant adjustment of said weighted cross correlation signals (31, 32, 33) to compensate a delay (τ) of the signal of a rake finger (9, 10, 11) being a time variant delay (τ) of a fading multipath signal.

21. Method for signal processing in a rake receiver according to one of claims 13 to 20, characterized in that said timing error detector (12) is an early late gate error timing detector and early and late estimates are subtracted and multiplied with reconstructed transmitted symbols (23).

22. Method for signal processing in a rake receiver according to claim 21 characterized in that said reconstructed symbols (23) are generated by complex conjugately multiplying symbol decisions or pilot symbols with estimates of the channel phase or the channel phasor.

23. Method for signal processing in a rake receiver according to claims 21 or 22 characterized in that the real part of the signal resulting from early and late estimate subtraction and multiplication with the reconstructed transmitted symbols (23) is used as

14-01-2000

EP00300268.0

CLMS

35

the generated error signal x .

24. Method for signal processing in a rake receiver
according to one of claims 13 to 23

- 5 characterized in that said error signal (x , 13) is fed
through a loop filter with lowpass characteristic to yield an
estimate $E(x)$ for the timing delay (τ).

THIS PAGE BLANK (USPTO)

Abstract

The invention is directed to a method for signal processing in a rake receiver for spread spectrum signals and is
5 directed to a rake receiver for spread spectrum signals comprising a plurality of rake fingers (9, 10, 11) each rake finger being adapted to receive a signal (7, 8) being part of a multipath signal (2) and associated with a path of the
10 multipath, said signal (7, 8) having a delay (τ) relative to an other signal associated with an other path of the multipath (7, 8), said receiver comprises a summation unit (37) for generating an output signal from the signals received from of at least some of the rake fingers (9, 10, 11), said output signal being a summation signal having and
15 improved signal to noise ratio (SNR) if compared with the signal to noise ratio (SNR) of at least one of the rake fingers (9, 10, 11), a timing error detector (12) for detecting a delay (τ) between signals of at least two rake fingers (9, 10, 11) and for generating a timing error signal
20 (x, 13) which is sent to a unit (6) for compensating the error of the respective delay (τ); to provide a code-tracking unit for a direct-sequence code division multiple access (DS-CDMA) receiver having an improved tracking performance, especially in cases where delay times of multipath signals
25 are in the order of the chip duration said timing error detector (12) generates a timing error signal (x, 13) based on the signals (7, 8) associated with paths of the multipath of more than one rake finger (9, 10, 11).

THIS PAGE BLANK (USPTO)




Figure 1: Digital code-tracking loop

14-01-2000

EP000300268.0

DRAW




Figure 2: Conventional coherent early-late TED




Figure 3: Conventional noncoherent early-late TED




Figure 4: Adaptive early-late TED concept




Figure 5: Adaptive FIR realization of the new coherent early-late TED




Figure 6: Adaptive FIR realization of the new noncoherent early-late TED




Figure 7: Detector characteristic for conventional TED




Figure 8: Detector characteristic for adaptive TED




Figure 9: Characteristic of outer FIR taps




Figure 10: S-Curve for EL extension: zero-crossing at $2T_c$




Figure 11: S-Curve for EL extension: zero-crossing at T_c




Figure 12: Timing tracking estimates, conventional TED, indoor, SF=4, 10 km/h




Figure 13: Timing tracking estimates, simple adaptive TED, indoor, SF=4, 10 km/h




Figure 14: Timing tracking estimates, MMSE adaptive TED, indoor, SF=4, 10 km/h




Figure 15: Tracking performance, indoor, SF=4, 10 km/h




Figure 16: RAKE receiver model

